

# Lightspecs – Sentrum Scene – Oslo Norway

Updated: 16 November 2018

- |   |  |
|---|--|
| 1x GrandMa 2 Light, Latest version  | 6x Clay Paky Alphaspot 1500 HPE        |
| 66x 3KW Standard 8 bit dimmer channels,<br>Various fan in/outs available. | in 36 channel standard mode            |
| 16x 1KW Par 64, CP61 in standard plot                                     | 12x Clay Paky K10 B-Eye                |
| 8x 1KW Par 64, CP61 available   | in 35 channel shapes mode              |
| 12x ETC Source Four 750w Zoom (25-50)                                     | 3x Atomic 3000 strobes                 |
| 4x Two way 4-lights blinders (4x 650W)                                    | 1x Juliet Corrigan HMI 1200 followspot |
|   | 1x MDG Atmosphere H.O                  |
|   | 1x Look Unique II Hazer                |

## **Curtains:**

Stage is boxed in with black backdrop (approx 1,5m upstage center edge) and black leg son each side. Motorized front curtain, approx 3m from downstage center edge.

## **POWER:**

There is a **total** of 350A/400V 3phase available for use through following distributions.  
20x16A/230V in dimmer patch. (available as wieland, schuko or 16A CEE)  
1x16A CEE, 2x32A CEE, 4x63A CEE, 1x125A CEE, 1x125A Camlock (Use of camlock requires electrician on duty). Please note: 3x63A CEE are already in use by in-house dimmers. 1x32A CEE are already in use by LX2-LX5 motors. 1x16A CEE are already in use by LX1 + PA motors. But available if not needed for in-house equipment.

## **MULTICABLES:**

Soca 6 channel multicables from patch to: LX1 x 3, LX2 x 5, LX3 x 5, LX4 x 5. One on each side downstage.

## **SIGNAL PATCH:**

### **DMX universe distribution from FOH:**

Universe 1 – 8 through ArtNet node. Node address: IP 2.10.10.2 / 255.0.0.0

Universe 1: Dim	Universe 3: LX2	Universe 5: LX4	Universe 7: Floor stg.R
Universe 2: LX1	Universe 4: LX3	Universe 6: Floor stg.L	Universe 8: Free

Additional 4 separate wired DMX lines from FOH to stage available for guest use

2 RJ45 Cat 6 line from FOH to stage available. Breakout from RJ45 to 4 dmx lines available on request.  
Note: 1 line in use by in-house artnet node. Available when node not in use.

## **Standard Patch:**

See standard light plot for patch.

Standard light plot with patch found here: <http://www.rockefeller.no/specs/lightplotsentrum.pdf>

MA2 showfile with standard patch: <http://www.rockefeller.no/specs/sentrumstdpatch3d.show.gz>

## **RIGGING:**

For rigging information please see rigging plot for details.

Rigging plot with venue measurements here: <http://www.rockefeller.no/specs/riggplotsentrum.pdf>